

THE ENGLISH ELECTRIC CO., LTD.

NELSON RESEARCH LABORATORIES

STAFFORD

MATHEMATICAL PHYSICS LABORATORY.

Report No. NS t 39

Date 30.11.55.

Reference

Order No.

Telephone:—Stafford 700.

Front Sheet.

Data Sheet 1

Figure sheets S6/10331 and S6/10355

DEUCE Subroutine No. 108 (R03/1).

Report by
S.J.M. Denison.

SUMMARY.

The attached document contains details of a subroutine for reading and scaling three 9-digit decimal numbers from a card. It has been prepared, tested and copied into all instruction delay lines at N.R.L. Blackheath.

S.J.M. Denison

MATHEMATICAL PHYSICS LABORATORY.

NELSON RESEARCH LABORATORIES
STAFFORD E. E. CO. LTD.

NS t 99

Sheet No.: 1.

Description. Reads three 9-digit decimal numbers from a card, converts them to binary and multiplies them by a given scaling factor. i.e. will convert from a specified No. of decimal places to a specified No. of binary places.
First order.

Data. a,b,c, signed 9-digit decimal numbers with D decimal places, punched with signs in cols. 1, 11, 21 and digits in columns 2-10, 12-20 and 22-30.

Result. ka, kb, kc in binary (or a,b,c, to p binary places).

Failure. 9-24) Card not decimally punched.

Error. $\pm \frac{1}{2} P.1.$

<u>Useful scaling factors.</u>	<u>D</u>	<u>p</u>	<u>$10^{-D} \cdot 2^{p+30}$</u>
	0	0	P31
1	4	6, 19, 25, 12, 6, 19, 1	
2	7	31, 8, 1, 23, 30, 8, 1	
3	10	12, 26, 13, 18, 24, 0, 1	
4	14	12, 29, 2, 23, 13, 20, 1	
5	17	4, 17, 21, 5, 30, 9, 1	
6	20	3, 20, 23, 23, 17, 1, 1	
7	24	11, 19, 18, 31, 21, 21, 1	
8	27	9, 28, 14, 12, 30, 10, 1	
9	30	1, 29, 11, 16, 11, 2, 1	
10	34	7, 27, 31, 6, 31, 22, 1	


Uses. 0 13-0 0 0 in 1₂₈

Time:- $1\frac{1}{2}$ m.s. before Y-row single shot.
 $18\frac{1}{2}$ m.s.(max) after 9-row single shot


Instructions for Use.

Stores Used. 13 14 15 16 19 20 21₂ 21₃ 30,1,2
 Contents at Entry. Link - - - - -
 Contents at Entry. ka kb kc |c| 65P₁₇ - 0 |kc| ka, kb, kc
 Occupies. D.L. 2, 3₀₋₂₉, 4₆₋₃₁ + 4₂ and 4₃ (instructions more than R03)
 Entry. 4₂₁
 Parameter. k $10^{-D} 2^{30}$ in 4₇ (k = 2^p to produce a,b,&c to p binary places)
 Constants etc. available. 21-0 1 0 13 in 4₁₄
 21-0 0 0 in 2₂₈
 P₂₋₁₀, P₁₂₋₂₀, P₂₂₋₃₀ in 2₁₂
 65 P₁₇ in 4₂₅
 in:- 3₂₆ 4₁₈ 4₁₁ 2₄ 4₂₉ 3₂₂ 3₁₅
 are:- 10² 10³ 10⁴ 10⁵ 10⁶ 10⁷ 10⁸ x P.1.
 Waste instruction. 1 0-0 0 22 in 4₆


NOTE. Read is not cleared in the subroutine, but the waste instruction may be used for this.



In a column where the decimal digit has not yet occurred, add the appropriate power of 10. When, and after the digit occurs do nothing.



all these numbers been dealt with on this row. so prepare to read the next row.



FORM DIAGRAM FOR SUBROUTINE NO 108 (R03/1)
Read and scale 3, 9-digit numbers

